

MP250UB Mini Mixer Amplifier



Features

- Built-in Bluetooth, radio and USB function.
- 2 MIC IN, 2 EMC IN, 2 LINE IN, 1 LINE OUT.
- 100V or 70V constant voltage output, 4Ω~16 Ω constant resistance output.
- Support IR remote control.
- With priority function, priority is EMC/MIC1>AUX1/AUX2/MIC2.
- With master volume control, and individual volume control of MIC & LINE, as well as treble and bass volume control.

Specifications

Model	MP250UB
Power Supply	AC110-120V / AC220~240V 50/60Hz(Select via the switch)
MIC1 IN Sensitivity	10mV±10%
MIC2 IN Sensitivity	15mV±10%
AUX1 IN Sensitivity	350mV±10%
AUX2 IN Sensitivity	350mV±10%
EMC IN Sensitivity	350mV±10%
MIC Frequency Response	200Hz ~ 10kHz (±3dB)
AUX Frequency Response	100Hz ~ 16kHz (±3dB)
Noise	<10mV
Distortion	<1% 1KHz
Treble Adjustment	10dB (±2)
Bass Adjustment	10dB (±2)
Rated Output Power	250W
Interface Output Voltage	70V,100V(Constant voltage output).
Machine Dimension (D×W×H)	250×230×66mm
Package Dimension	363×292×106mm (1PC)
Maximum Package Dimension	610×390×240mm (4PCS)
Net Weight	3KG
Gross Weight	3.7Kg (1PC)